

Technical Specifications

Power Supply	9...28VDC PELV
Maximum Loxone Air Devices	128
Antenna	External stub-antenna provided
Power Consumption	max. 150mW
Total Power Loss	max. 150mW
Safety Protection	IP20
Ambient Temperature	-40...70°C / -40...158°F
Humidity	95% r. H. (non condensing)
Radio Frequency	868MHz (SRD Band Europe), 915MHz (ISM Band Region 2) max. Power 3.16mW
Dimensions	35.5x88x57mm / 1.4x3.46x2.24" (LxWxH)
Maintenance & Cleaning	The device is free of maintenance and may only be cleaned with a dry cloth.

LOXONE

Need Help?

loxone.com/support

Loxone Electronics GmbH
Smart Home 1
4154 Kollerschlag
Austria

loxone.com



V221119

LOXONE



Air Base Extension

Part No: 100114

About the product

Connect up to 128 Loxone Air devices using the Air Base Extension.

Features

- 128 Air devices

Installation

The installation of the device has to be mounted on a DIN rail in an electrical distribution housing and may only be performed by qualified personnel.

Protection against electrical contact and fire protection must be provided in the final installation by the use of a standard compliant/approved housing.

If the unit is used in a non conform manner as specified by the manufacturer the product included safeguards will be impaired.

This folder is a part of the product!



For additional information, declaration of conformity, visit www.loxone.com/help/air-base-extension

Connection

Wire Diameter	0.25...0.8mm ² / AWG23...AWG18
Exposed Wire Length	5mm / 0.2"
Push-In-Technology	To make connection, insert wire. To remove the wire, twist and pull the wire at the same time.

Information

Contains FCC ID: COR-ZWIR4512AC1

This device complies with part 15 of the FCC Rules.

Operation is subject to the following two conditions:

1. This device may not cause harmful interference
2. This device must accept any interference received, including interference that may cause undesired operation

